


Bill Printer MacOS Driver Documentation



1. Introduction

prt.pos.drv is the MacOS system driver installation package, which, when installed successfully, can be used with Neutral's 58 Series and 80 Series bill printers. This document provides instructions for driver installation, uninstallation, printer driver selection, and printer parameter introduction.

2. Install Bill Driver

Open the prt.pos.drv installation package in the Apple MacOS operating system. Follow the installation instructions, and when the installation page displays the message of successful installation, the installation process is complete.







3. Printer Select Driver

3.1 Automatic Printer Driver Matching


MacOS system operation method:

After installing the driver, connect the Neutral 58 or 80 series bill printer. Choose the Apple menu > "System Preferences" and select "Printers & Scanners." In the printer and scanner list, you will see the displayed Printer POS-58 or Printer POS-80 printer, which has been automatically added and matched with the corresponding driver. This confirms the successful installation of the printer driver, and you can proceed with printing operations.



CUPS Print Management System Operation Method:

To connect the printer device, open a browser and enter the URL "localhost: 631" to access the CUPS printing management system. Select "Printers" to enter the printer devices page, where you can see the printer name, driver name, and printer status. If you have connected a 58/80 series bill printer model that is supported by the driver, it will automatically install and match the driver (Printer POS-58 or Printer POS-80) upon printer connection, and you can view it on the "Printers" page.



CUPS.org Home Administration Classes Help Jobs **Printers**

打印机

Search in Printers: Search Clear

Showing 1 of 1 printer.

Queue Name	Description	Location	Make and Model	Status
Printer_POS_80	Printer POS-80	kim的Mac	POS-80	Idle

CUPS and the CUPS logo are trademarks of Apple Inc. Copyright © 2007-2019 Apple Inc. All rights reserved.

CUPS.org Home Administration Classes Help Jobs **Printers**

Printer_POS_80

[Printer_POS_80](#) (Idle, Accepting Jobs, Not Shared)

Maintenance Administration

Description: Printer POS-80
Location: kim的Mac
Driver: POS-80 (grayscale)
Connection: usb:///Printer/POS-80?location=1600000
Defaults: job-sheets=none, none media=custom_71.97x209.9mm_71.97x209.9mm sides=one-sided

Jobs

Search in Printer_POS_80: Search Clear

Show Completed Jobs Show All Jobs

Jobs listed in print order; held jobs appear first.


CUPS and the CUPS logo are trademarks of Apple Inc. Copyright © 2007-2019 Apple Inc. All rights reserved.


3.2 Manually Adding a Printer and Selecting the Drive

MacOS system operation method:

To connect a Neutral 58 or 80 series bill printer, choose the Apple menu > "System Preferences" and select "Printers & Scanners." Below the printer and scanner list, click the add button "+" and select the printer. Expand the "Use" section and click "Select File" to expand all installed drivers. If

the POS-58 or POS-80 drivers are included, it indicates that the driver installation was successful. Select the driver and click "Add" to complete the printer addition. You will see the printer in the printer and scanner list.





CUPS Print Management System Operation Method:

Open a browser and enter the address localhost: 631> "Administration" and select "Add Printer" to add a printer. You can add a new printer and select the driver. In "Local Printers," select the desired printer. Enter the printer name in the "Description" field. Under "Make," select "POS" from the drop-down menu and choose the corresponding printer driver. Finally, click "Add Printer" to complete the driver selection.

[CUPS.org](#) [Home](#) [Administration](#) [Classes](#) [Help](#) [Jobs](#) [Printers](#)

Administration

Printers

[Add Printer](#) [Find New Printers](#) [Manage Printers](#)

Classes

[Add Class](#) [Manage Classes](#)

Jobs

[Manage Jobs](#)

Server

[Edit Configuration File](#)

Server Settings:

[Advanced ▶](#)

☐ Share printers connected to this system

☐ Allow printing from the Internet

☐ Allow remote administration

☐ Use Kerberos authentication ([FAQ](#))

☐ Allow users to cancel any job (not just their own)

☐ Save debugging information for troubleshooting

[Change Settings](#)

CUPS and the CUPS logo are trademarks of Apple Inc. Copyright © 2007–2019 Apple Inc. All rights reserved.

Add Printer

Add Printer

Local Printers: ☒ Printer POS-80 (Printer POS-80)

Discovered Network Printers: ☐ HP LaserJet M128fn 161[BED70F] (Hewlett-Packard HP LaserJet Pro MFP M128fn)
☐ HP LaserJet M128fn 166 [E3ABFD] (Hewlett-Packard HP LaserJet Pro MFP M128fn)
☐ HP LaserJet M203dn (AB93F8) (HP LaserJet M203-M206)
☐ HP LaserJet Pro MFP M128fn[EF977C] (Hewlett-Packard HP LaserJet Pro MFP M128fn)
☐ HP LaserJet Pro MFP M128fn[RM] (Hewlett-Packard HP LaserJet Pro MFP M128fn)
☐ M128fn169 (Hewlett-Packard HP LaserJet Pro MFP M128fn)

Other Network Printers: ☐ Internet Printing Protocol (http)
☐ Internet Printing Protocol (ipp)
☐ Internet Printing Protocol (ipps)
☐ Internet Printing Protocol (https)
☐ LPD/LPR Host or Printer
☐ AppSocket/HP JetDirect
☐ Windows printer via spoolss

[Continue](#)

Add Printer

Add Printer

Name:

(May contain any printable characters except "/", "#", and space)

Description:

(Human-readable description such as "HP LaserJet with Duplexer")

Location:

(Human-readable location such as "Lab 1")

Connection:

Sharing: ☒ Share This Printer

[Continue](#)

Add Printer

Add Printer

Name: Printer_POS-80
Description: Printer POS-80
Location:
Connection: usb://Printer/POS-80?location=1710000|Printer POS-80
Sharing: Share This Printer
Make: DYMO
Epson
Generic
HP
Intellittech
Oki
POS
POSAuto
Raw
Zebra
Continue

Or Provide a PPD File: Choose File no file selected
Add Printer

CUPS and the CUPS logo are trademarks of Apple Inc. Copyright © 2007–2019 Apple Inc. All rights reserved.

Add Printer

Add Printer

Name: Printer_POS-80
Description: Printer POS-80
Location:
Connection: usb://Printer/POS-80?location=1710000|Printer POS-80
Sharing: Share This Printer
Make: POS Select Another Make/Manufacturer
Model: POS-58 (en)
POS-76 (en)
POS-80 (en)

Or Provide a PPD File: Choose File no file selected
Add Printer

CUPS and the CUPS logo are trademarks of Apple Inc. Copyright © 2007–2019 Apple Inc. All rights reserved.

4. Printer Management

Printer Status Adjustment


In the CUPS Print Management System page, select "Printers" to enter the printer device page. Click "Maintenance" to expand the dropdown menu. You can use the following functions to adjust the printer status:

"Print Test Page";

"Pause Printer/Resume Printer";

"Reject Jobs/Accept Job";

"Move All Jobs";
"Cancel All Jobs".




Printer Parameter Settings

CUPS Print Management System Operation Method:


Click "Administration" to expand the dropdown menu. You can modify printer parameters using the following settings:

"Modify Printer";
"Delete Printer";
"Set Default Options"
"Set As Server Default";
"Set Allowed users".



"Modify Printer";

Select the desired printer in "Local Printers," enter the printer name in the "Description" field, select "POS" under "Select Another Make/Manufacturer," and choose the corresponding printer driver. Finally, click "Modify Printer" to complete the driver selection.



CUPS.orgHomeAdministrationClassesHelpJobsPrinters

localhost

⏏+⛶

Modify Printer

Modify Printer_POS_80

Description:Printer POS-80
(Human-readable description such as "HP LaserJet with Duplexer")

Location:kim@Mac
(Human-readable location such as "Lab 1")

Connection:usb://Printer/POS-80?location=1600000

Sharing:☐ Share This Printer

Continue

CUPS and the CUPS logo are trademarks of Apple Inc. Copyright © 2007–2019 Apple Inc. All rights reserved.

CUPS.orgHomeAdministrationClassesHelpJobsPrinters

localhost

⏏+⛶

Modify Printer

Modify Printer_POS_80

Description:Printer POS-80

Location:kim@Mac

Connection:usb://Printer/POS-80?location=1600000

Sharing:Do Not Share This Printer

Make:POS


Model:

Current Driver – POS-80
POS-80 (en)
POS-58 (en)
POS-76 (en)

Or Provide a PPD File: no file selected

Modify Printer


CUPS and the CUPS logo are trademarks of Apple Inc. Copyright © 2007–2019 Apple Inc. All rights reserved.



"Set Default Options"


General (General)

Paper Size: Set the paper size for printing. The list includes preset paper sizes, or you can choose "Custom" to customize the paper size.




Effect (Effect)

1. Brightness: -50, -40, -30, -20, -10, 0, 10, 20, 30, 40, 50 can be set
2. Dithering: Choose between "None" and "Error Diffusion"




Cut Option (Cut Option)

1. Page Cut Type (Page Cut Type): You can set "No Cut" (Do not perform cutting), "Partial Cut"(Partial Cut means Perform partial cutting), or "Full Cut" (Cut it all off). If the printer only has the "Full Cut" function, setting "Partial Cut" will have no effect, and the printer will still perform a full cut. Similarly, if the printer only has the "Partial Cut" function, setting "Full Cut" will have no effect.
2. Document Cut Type (Document Cut Type): You can set No Cut (No Cut), Partial Cut (Perform partial cutting), and Full Cut (Cut it all off).
3. Feed Cut After Job End (Feed Cut After Job End): The length of the paper left after cutting is adjustable. It can be set to "None" (None) for no extra paper, or select 1 Line-15 Line (1-15 lines) to leave as extra paper




Cash Drawer Control (Cash Drawer Control)

1. Cash Drawer 1 (Cash Drawer 1): Not Cash Drawer 1 (Not Cash Drawer), Cash Drawer 1 Before Printing (Cash Drawer Before Printing), Cash Drawer 1 After Printing (Cash Drawer After Printing). The printer needs to be connected to the cash drawer before setting this function.
2. Cash Drawer 2 (Cash Drawer 2): Not Cash Drawer 1 (Not Cash Drawer), Cash Drawer 1 Before Printing (Cash Drawer Before Printing), Cash Drawer 1 After Printing (Cash Drawer After Printing)






Buzzer Control (Buzzer Control)


1. Document Buzzer (Document Buzzer): You can set No Use (No Use), Document Before (Document Before), Document After (Document After)
2. Page Buzzer (Page Buzzer): You can set No Use (No Use), Document Before (Document Before), and Document After (Document After)
3. Buzzer-On Time (Buzzer-On Time): 50-450 milliseconds (ms)
4. Buzzer Repeat (Buzzer Repeat): 1-9 times



Printer parameter settings can also be configured in the Mac system. When encountering a preview window while printing web pages, memos, PDFs, documents, or spreadsheets, click on "Show Details" first. In the drop-down menu, select "Printer Features" to modify the default driver settings.







5. Uninstall Bill Driver

To delete the POS and PPDs folders, go to the main page and select "Go" > "Computer" > "Hard Drive" > "Library" > "Library" > "Printers". Move the POS and PPDs folders to the trash bin for deletion. After deleting them, the automatic installation of Neutral bill printers will no longer be possible, or adding a printer with the Make printer option will confirm successful driver deletion. In the printer and scanner list, click the add button "+" below, select the printer, expand the "Use" section, and click "Select File". If the Printer POS-58 or Printer POS-80 is not available in the file selection window, it indicates successful driver deletion.

