Customize the Paper's Specifications

According to personal needs, clients could alter the paper's size by their own. Take WIN7 operating system for an example. The specific operations are as follows.

1. Click the icon of the installed printer under the "Devices and Printers". Then choose the "Printer Service Properties".



2. After the menu popping up, firstly find the format of the paper's specifications which has been installed through the printer driver. Next, some operations could be taken as the following picture shown.

) mm 7 mm			-	Delete
mm				Delete
/6 mm				
			-9	Save Form
ew form form by ed its. Then clic iption (meas	iting the exis ck Save Form surements) –	sting name an n.	nd	
© <u>M</u> et	ric	English		
01. 280 D	Printer are	a margins:		
2.84in	Left:	0.00in	Top:	0.00in
16.54in	<u>R</u> ight:	0.00in	Bottom:	0.00in
	80(7 form by ed ts. Then clic ption (meas <u>Met</u> 2.84in 16.54in	80(72.1) x 420 m ew form form by editing the exis ts. Then click Save Form ption (measurements) <u>Metric</u> <u>Printer are</u> 2.84in <u>Left:</u> 16.54in <u>Right:</u>	80(72.1) x 420 mm 5 iew form form by editing the existing name ar its. Then click Save Form. ption (measurements) Metric Printer area margins: 2.84in Left: 0.00in 16.54in Bight: 0.00in	80(72.1) x 420 mm 5 ew form form by editing the existing name and ts. Then click Save Form. ption (measurements) Metric <u>Metric</u> <u>English</u> Printer area margins: 2.84in <u>Left:</u> 0.00in <u>I</u> op: 16.54in <u>Bight:</u> 0.00in <u>Bottom</u> :

3. After finishing the above settings, click the "Save Menu" button. The Form's name which has already been set up could be found in the tab of "Form". As the following picture shown. Then, close the dialog box.

ms Ports	Drivers S	ecurity Adva	anced		
orms on:	JXAF-PC				
80(72.1) x 21(80(72.1) x 20	0 mm			-	<u>D</u> elete
80(72.1) x 32	76 mm		_		
30(72.1) × 420) mm			•	Save Form
Form <u>n</u> ame:	80(7	2.1) x 420 mi	m		
Create a r Define a new measuremer	ew form form by ed its. Then cli	iting the exis ck Save Form	sting name ar 1.	nd	
✓ Create a r Define a new measuremer Form descri Units:	form by ed form by ed its. Then cli- iption (mea:	liting the exis ck Save Form surements) – ric	sting name ar n. English	nd	
✓ <u>C</u> reate a r Define a new measuremer Form descri Units: Paper size:	form by ed form by ed its. Then cli- ption (mea: <u>M</u> et	liting the exis ck Save Form surements) – ric Printer are	sting name ar n. © <u>E</u> nglish ea margins:	nd	
✓ <u>C</u> reate a n Define a new measuremen Form descri Units: Paper size: <u>W</u> idth:	form by ed form by ed its. Then cli- ption (mea: <u>Met</u> 2.84in	liting the exis ck Save Form surements) ric Printer are Left:	sting name ar n. <u>English</u> a margins: 0.00in	Iop:	0.00in
☑ <u>C</u> reate a r Define a new measuremer Form descri Units: Paper size: <u>W</u> idth: <u>H</u> eight:	ew form form by ed its. Then cli- iption (mea: <u>Met</u> 2.84in 16.54in	liting the exis ck Save Form surements) ric Printer are Left: <u>R</u> ight:	e margins:	Iop: <u>B</u> ottom:	0.00in 0.00in
✓ <u>C</u> reate a r Define a new measuremer Form descri Units: Paper size: <u>W</u> idth: <u>H</u> eight:	ew form form by ed its. Then cli ption (mea <u>Met</u> 2.84in 16.54in	liting the exis ck Save Form surements) ric Printer are Left: <u>R</u> ight:	 English Tangins: 0.00in 	Iop: Bottom:	0.00in 0.00in

4. Enter "Devices and Printers", and press the right mouse on the option of "Printer Properties" . After the dialog box popping up, choose the "Preferences" option.

Shann	g Ports Ad	dvanced	Color Management	Security	Device Settin
-	POS-80C				
Location:					
Comment:					
Model:	POS-80C				
Features					
Color: No		Paper available:			
Double-sided: No Staple: No			80(72.1) × 297	80(72.1) x 297 mm	
Speed: Unk	nown				
Maximum	resolution: 20	3 dpi			π.
		Pro	eferences	Print	Test Page
			ar ar ar ra agrin	7101	restrage

5."Paper/Quality"—"Advanced" . See the following picture.

POS-80C Printing Pr	eferences
Layout Paper/Quality	
Tray Selection	
Paper <u>S</u> ource:	Automatically Select
	Ad <u>v</u> anced
	OK Cancel Apply

6. Find the new paper size which was set in the "Paper Specifications" . Press the "OK" button and close the dialog box. See the following picture.

POS-80C Advanced Options	X
POS-80C Advanced Document Settings Paper/Output Paper Size: 80(72.1) x 420 mm Copy Count: <u>1 Copy</u> Document Options Advanced Printing Features: <u>Enabled</u> Pages per Sheet Layout: <u>Right then Down</u> Halftoning: <u>Auto Select</u>	
ОК	Cancel

7.Return to the tab of "Device Settings" and select "Paper Specifications" . Then click the "OK" button. See the following picture.

P D	OS-80C D)evice S o Tray A	ettings Assignment			
	Ma	nual Pa	per Feed: 8	30(72.1) x 297 mm	~	
	a installa	ble Opt	ions 🔽	3 Not Available		
	180	degree	s page rot	🗐 57 x 90 mm		
	Sav	e Paper	Mode: Bo	58(48) x 3276 mr	n	
	Cas	hbox A	ction: <u>Nor</u>	80(72.1) x 210 m	m	
	Pap	er Cutt	ing Action	80(72.1) x 297 m	m	
	Prir	nt dardr	ess: <u>Defau</u>	80(72.1) x 3276 n	nm	
	Tur	n on ale	rting: <u>Turr</u>	80(76) x 3276 mr	n	
	Fee	ding aff	er page pr	32(80) x 3276 mr	n	
	Iop	LOGO	ID: None			
	Iop	LUGO	CO ID Node:	Normal		
	BOU	tom LO	GO ID: None	der Mannal		
	DOL	tom LO	GO Print Mit	de: <u>Normai</u>		